

Aurora UPS

Reliable Power Protection with standard battery backup



The Eaton Aurora Line-Interactive UPS affordably protects critical applications from downtime, data loss and corruption caused by power fluctuations and outages.

With built-in Double Boost and Buck Automatic Voltage Regulation, the Aurora is perfect for areas where the supply voltage is constantly unstable.

Designed for IT applications requiring standard power backup time, the Aurora features a microprocessor controller for managing power.

Product Snapshot

Power Rating : 600/1000 VA
Configuration : Tower
Voltage : 230V
Frequency : 50 Hz
Technology : High-frequency line-interactive

Features

- Microprocessor controller design assures maximum reliability and stability
- Double Boost & Buck voltage regulation provides stabilised output
- Stepped sine wave provides high efficiency
- Wide input-voltage range appropriate for the harshest electrical environments
- Up to 4 India type 5A output receptacles
- Auto-restart function
- Cold start on battery power allows portable power
- Compact design is perfect for placement on or under a desk
- Green Power function prevents battery discharge when no load is present

Line-Interactive topology

This topology guarantees consistent reliability and high level of power quality. Whatever the supply disturbances, the output waveform is stabilised via double boost and buck mode. The battery is used only as a backup source.

High performance and reliability

Aurora features a microprocessor controller that delivers modified sine wave output offering the highest levels of reliability and efficiency, all in a compact design.

Wide Input-voltage range

Aurora has a very wide input voltage range of 140-300V, which reduces the number of transfers to battery power.

Cold start on battery power

This function ensures trouble free start-up of your applications even during a utility power outage.

Auto restart function

When AC power returns the UPS will automatically restart without user intervention.

Overload protection

Alerts the user and prevents the UPS from being damaged.



Powering Business Worldwide

Technical Specifications

| Model : VA/Watts | | 600VA/360W | 1000VA/500W |
|---|--|--|---|
| Technology | | Line - Interactive with Microprocessor Controlled Design | |
| Input / Output | | | |
| Nominal Input Voltage | | 230Vac 1 Phase | |
| Input Voltage Window @ full load | | 140 - 300Vac (load dependent) | |
| Input Power Factor | | 0.98 | |
| Frequency & Frequency Range | | 50+/- 1Hz | |
| Nominal Output Voltage | | 230V | |
| Output Voltage on Battery | | +10 % / -10% | |
| Output Waveform | | Modified sine wave | |
| Input Connection | | C14 5A | |
| Output Receptacles | | (3) IN 5A | (4) IN 5A |
| Battery | | | |
| Battery Quantity | | 1 x 12V/7AH x 1 | 1 x 12V/7AH x 2 |
| Re-charge Time to 90% Capacity | | 6 hours | |
| Battery Backup Time* (At a PC load with 15" monitor) | | 15-20 minutes | 30-35 minutes |
| Start-on-Battery | | UPS can be started without being connected to AC utility power | |
| User Interface | | | |
| Visual | | Line Mode: Green LED Lighting Battery Mode: Green LED Flashing Fault: None | Line Mode: Green LED Lighting Battery Mode: Yellow LED Flashing Fault: Red LED Lighting |
| Control | | One button for On/Off | |
| Environment | | | |
| Operating Temperature | | 0°C ~ 40°C | |
| Storage Temperature | | -15°C ~ 50°C | |
| Humidity | | 0 ~ 90% | |
| Noise Level | | <40dB | |
| Dimensions & Weights W x H x D mm | | | |
| Models (W x H x D) mm | | 278 x 100 x 143 | 342 x 133 x 180 |
| Gross Weight (kg) | | 5.4 | 10.23 |

In the interest of continuous product improvement, all specifications are subject to change without notice.

*Battery backup times are approximate and may vary with equipment, configuration, battery age, temperature, etc.



Headquarters

**Eaton's Electrical Sector
Americas Region**
8609 Six Forks Road Raleigh, NC 27615 U.S.A

South Asia Office

**Eaton's Electrical Sector
Eaton Power Quality Pvt. Ltd.**
6th Floor, Tower- B,
Plot No. 8, Sector - 127, Noida - 201301
Tel: +91 - 0120 - 3855300
Sales and Service
Toll Free Hotline.: 1800 200 7887
E-mail: EatonPowerQualityIndia@eaton.com

www.eaton.com • www.powerquality.eaton.com

Offices Across India

Mumbai
EL Floor, VITS Luxury Business Hotel,
Andheri Kurla Road, Andheri (East),
Mumbai - 400 059
Tel : +91-22-4005 3817
Fax: +91-22-4005 3810

Chennai
No. 22, Chamier's Road,
Block "D" Ashika Chambers,
Teynampet, Chennai - 600 018
Tel : +91 44 2432 0249-50
Fax: +91 44 2432 0249

Bangalore
Unit No. 501, 4th Floor,
Prestige Atrium, Central Street,
Bangalore - 560 001
Tel : +91 80 4901 2200
Fax: +91 80 4901 2239

Ahmedabad: +91 932 703 1597
Chandigarh: +91 172 501 1578
Coimbatore: +91 934 541 9578
Cochin: +91 934 982 1582
Gurgaon: +91 124 410 0047
+91 124 436 6315
Hyderabad: +91 40 4018 9601
Kolkata: +91 33 4004 0968
Pune: +91 20 3061 1886

Sales and Service Operations

Sri Lanka:
+94 112871000
+94 117520031

Nepal:
+97 714429777
+97 714429888
+97 714423376

Bangladesh:
+8802 7170368, 7162568, 7162619
+8802 9347918, 9330765, 9348220